

ICOM T7H QUICK REFERENCE 6/24 KH7O

[H/L]1s for SETTINGS mode
[H/L] toggle for different parameters
[DIAL] to change value
[VFO] quick press to EXIT

////////////////////////////////////
EXAMPLE 146.86- TONE 88.5 TO MCH 5
[VFO] quick press if in MR mode
keyboard enter 146.860 or dial to freq
set OFFSET 0.600
set DUP or SIMPLEX
set TONE TYPE
[S.MW] quick press "MR" blinks
dial to Memory CH 5
[S.MW] long press saves to MCH
[MR] to switch to MCH

////////////////////////////////////
TONE FREQUENCY
[H/L] 1s to get into set mode
[H/L] toggle for rT
[DIAL] to change value
[VFO] quick press to EXIT
////////////////////////////////////
UNKNOWN TONE SCAN
[TSCAN] hold till scan starts

////////////////////////////////////
CTCSS FREQUENCY
[H/L] 1s to get into set mode
[H/L] toggle for CT
[DIAL] to change value
[VFO] quick press to EXIT

////////////////////////////////////
SCAN PAUSE or HOLD
[H/L] 1s to get into set mode
[H/L] toggle for SC
[DIAL] to P-02 or T-10
[VFO] quick press to EXIT

////////////////////////////////////
BAND SWITCHING
[VFO] if in MCH mode
[BAND] toggle
////////////////////////////////////
VFO to MCH
[MR] quick press

////////////////////////////////////
TUNING STEPS
[H/L] 1s to get into set mode
[H/L] toggle for TS
[DIAL] to change value
[VFO] quick press to EXIT

////////////////////////////////////
CHANNEL SCAN SKIP
MR channel selected
[MR] 1s "skip" displays

////////////////////////////////////
DUPLEX or SIMPLEX
[TONE] hold until offset change
repeat above to next offset
////////////////////////////////////
MCH to VFO
[VFO] quick press

////////////////////////////////////
OFFSET KHZ/MHZ
[H/L] 1s to get into set mode
[H/L] toggle for OW
[DIAL] to change value
[VFO] quick press to EXIT

////////////////////////////////////
MONITOR
[MONI] hold for USQ
[MONI] tap twice lock OPEN

////////////////////////////////////
TONE TYPE
[TONE] toggle for type

INITIAL ONE TIME SETUP
[H/L] hold then power up
[DIAL] to set value
[H/L] toggle to next setting

VO Voltage display (ON)
P5 Power Save (OFF)
Ar auto repeater (ON 1 USA)
BE beep on speaker (OFF)
LI light mode (AUTO)
AO auto power off (OFF)
M5 mic simple (NORMAL)
LC set LCD contrast 91)
DT DTMF speed (100)
////////////////////////////////////
WIDE/NARROW
[H/L] 1s to get into set mode
[H/L] toggle for rT
[DIAL] to change value
[VFO] quick press to EXIT

////////////////////////////////////
DELETING MCH
[S.MW] quick press "MR" blinks
[DIAL] to MEM CH location
[S.MW] quickly followed by
[S.MW] hold down until blank screen

////////////////////////////////////
POWER OUT
[H/L] toggle
low/ BLANK=H
////////////////////////////////////