

# McMinnville Amateur Radio Club & Yamhill County ARES

 IC-7300 SSB Voice Setup & Audio Monitor Reference Card

Select SSB Mode

1. Tap **MODE**
2. Choose **USB** (20m+) or **LSB** (40m-)

 Turn OFF Compression

1. Press **MENU** → **SET**
2. Go to **Tone Control** → **SSB TX**
3. Set **COMP** to **OFF**

 Adjust Mic Gain

1. In **SSB TX** menu, set **MIC GAIN** (start at 50–55)
2. Tap **TX meter** on main screen → cycle to **ALC**
3. Speak into mic → Aim for **30–50% ALC**

 Enable Compression

1. In **SSB TX**, set **COMP** to **ON**
2. Adjust **COMP Level** (start around 2–3)
3. Tap **TX meter** → cycle to **COMP**
4. Speak → Aim for **10–20 dB COMP**

 Display Audio Scope

1. Press **MENU** → tap **SCOPE**
2. Tap **AUDIO** at bottom to view waveform

# McMinnville Amateur Radio Club & Yamhill County ARES

 IC-7300 SSB Voice Setup & Audio Monitor Reference Card

Select SSB Mode

1. Tap **MODE**
2. Choose **USB** (20m+) or **LSB** (40m-)

 Turn OFF Compression

1. Press **MENU** → **SET**
2. Go to **Tone Control** → **SSB TX**
3. Set **COMP** to **OFF**

 Adjust Mic Gain

1. In **SSB TX** menu, set **MIC GAIN** (start at 50–55)
2. Tap **TX meter** on main screen → cycle to **ALC**
3. Speak into mic → Aim for **30–50% ALC**

 Enable Compression

1. In **SSB TX**, set **COMP** to **ON**
2. Adjust **COMP Level** (start around 2–3)
3. Tap **TX meter** → cycle to **COMP**
4. Speak → Aim for **10–20 dB COMP**

 Display Audio Scope

1. Press **MENU** → tap **SCOPE**
2. Tap **AUDIO** at bottom to view waveform