

ICOM T70A QUICK REFERENCE

[DIAL]to parameter (skinny radio knob)
[VOL] to change value (wide radio knob)

[A/SET] quick press SET MODE
[B/BAND] quick press in VFO mode UHF/VHF
[C/HML] quick press RF power L /M/blank=H
[D/V/M/C] quick press VFO/MCH

KH7O 6/24

long press KEYBOARD LOCK
long press UNSQ
long press SCAN
long press "MR" blinks/ dial to MCH 2nd long press to store SEE BELOW

EXAMPLE: 146.86- tone 88.5 memory CH 5

[D] toggle from MCH to VFO
set TONE FREQUENCY "88.5"
set OFFSET "0.600"
set "DUP-"
set TONE TYPE "T"
[D] long press "MR blinks"
dial to Memory CH 5
2nd long press saves to MCH
toggle [D] for MCH /VFO
NOTE: power is not stored

////////////////////
TONE FREQUENCY
[A/SET] quick press
[DIAL] to parameter next line
R tone (T) encode
[VOL] to change value
[D] exit

////////////////////
SCAN PAUSE or HOLD
[A/SET] quick press
[DIAL] to parameter next line
PAUSE (scan hold/2 /20)
[VOL] to change value
[D] exit

////////////////////
VFO to/from MCH
[D] toggle

////////////////////
UNKNOWN TONE SCAN
[TSCAN] hold till scan starts

////////////////////
CTCSS FREQUENCY
[A/SET] quick press
[DIAL] to parameter next line
C tone (T SQL) enc/decode
[VOL] to change value
[D] exit

////////////////////
RESUME after PAUSE
[A/SET] quick press
[DIAL] to parameter next line
RESUME (time after pause)
[VOL] to change value
[D] exit

////////////////////
BAND SWITCHING
[D] toggle to VFO
[B] toggle to swich band
////////////////////

////////////////////
TUNING STEPS
[A/SET] quick press
[DIAL] to parameter next line
tS (tuning steps)
[VOL] to change value
[D] exit

////////////////////
CHANNEL SCAN SKIP
[A/SET] quick press
[DIAL] to parameter next line
P SKIP (turn ON to skip)
[VOL] to change value
[D] exit

////////////////////
DUPLEX or SIMPLEX
[DUP] hold until offset change
repeat above to next offset
////////////////////

////////////////////
OFFSET KHZ/MHZ
[A/SET] quick press
[DIAL] to parameter next line
OFFSET (.600/5.0)
[VOL] to change value
[D] exit

////////////////////
DTMF PTT + NUMBER
[A/SET] quick press
[DIAL] to parameter next line
dtmF (KEY for PTT+ NUM)
[VOL] to change value
[D] exit

////////////////////
TONE TYPE
[TONE] hold until type change
repeat above to next type
////////////////////

////////////////////
WIDE/NARROW
[A/SET] quick press
[DIAL] to parameter next line
modE (WIDE)
[VOL] to change value
[D] exit

////////////////////
MIC GAIN 4
[A/SET] quick press
[DIAL] to parameter next line
mic G (mic gain 1-4)
[VOL] to change value
[D] exit

////////////////////
POWER OUT
[C] toggle
L/ M/ BLANK=H
////////////////////