

Basic Voice Traffic Handling: Mechanics

Helen Straught
WC4FSU@ARRL.NET

C. Matthew Curtin
KD8TTE@ARRL.NET





Origination, Relay, and Delivery



Learning Objectives:

1. Describe steps of radio messaging
2. Identify references
3. Identify training options



Do Not Just Complete the Form Top to Bottom

Unless you like to make errors.

Forms impose organization on the medium (printed form on paper, or displayed form on screen).

Forms exist for the purpose of helping a person get information in the right *format*.

Format is organization of data to support exchange or storage.



Four Steps In Radio Messaging

Origination	Relay: Send	Relay: Receive	Delivery
<p>Prepare message for relay for someone else.</p> <p>(2) To (4) From (3) Text (1) Preamble</p> <p><i>Not radio stuff!</i></p>	<p>Send prepared message from your radio station to another radio station.</p>	<p>Receive prepared message from another radio station at your radio station.</p>	<p>Give the written message to the addressee ("To"), so it makes sense to them.</p> <p><i>Not radio stuff!</i></p>



Origination

Prepare message for relay
(usually for someone else).

Origination is organizing the thoughts of one person for transmission.

To (including how to get it there: phone, physical address, or station).

From (including how to reply: phone, physical address, or station).

Text (what to say).

Preamble (radio operators).



MPG 1.0.2 Example

Shows radiogram form with the “part” (or “block”) numbers in parens.

Origination part is in the bottom-left, part 7.

The origination record is so if someone asks how W1AW number 1 (this message) got created, the radio operator has recorded the name and contact information for the person who worked with the operator to make the message.

It also includes date and time, which could show a delay between creating the message and getting it to the sending operator.

PREAMBLE (1)							
[1]	[2]	[3]	[4]	[5]	[6]	[7]	[8]
NR	PREC	HX	STN ORIG	CK	PLACE OF ORIG	TIME FILED	MON DY
1	R	HXE	W1AW	12	NEWINGTON CT	1830Z	JUL 1
(2) TO DONALD R SMITH 164 EAST SIXTH AVE RIVER CITY MD 00789						THIS RADIO MESSAGE WAS RECEIVED AT: (9) AMATEUR STATION _____ TEL _____ NAME _____ STREET ADDRESS _____ CITY, STATE, ZIP _____	
TEL 301 555 3470							
OP NOTE (2.4)							
TXT (3)							
THANKS TO X						FOR SEE 73	
MESSAGE YOU						X AT	
						HOPE HAMFEST	
SIG (4) DIANA						OP NOTE (4.2)	
RCVD FROM		NET		DATE/TIME		SENT TO	
(5) WD3W		MEPN		012215Z JUL 91		(6) KD3JK	
						NET MDD	
						DATE/TIME 012308Z JUL 91	
(7) ORIG - FROM - DATE/TIME						(8) DLVD - TO - DATE/TIME	
Name						Name	
Addr						Addr	
City						City	
TEL						TEL	

There's no “radio stuff” yet.

Completion of the form helps to format the message for transmission.

Completion of the origination part helps to establish the record of where the message came from in the first place.



Standard Radiogram Form

What's happening?


There is no origination part!

You're right. Use "Received" (RECD) for origination on the standard form

In origination, you received a message and might have asked questions to get complete information for transmission.

Record who gave you the message and how (verbally? in-house phone? written?)...

Record date and time that you got the message.



The form is titled "THE AMERICAN RADIO RELAY LEAGUE RADIOGRAM VIA AMATEUR RADIO". It features two ARRL logos at the top corners. The form is divided into several sections: a header with fields for NUMBER, PRECEDENCE, HX, STATION OF ORIGIN, CHECK, PLACE OF ORIGIN, TIME FILED, and DATE; a "TO" section with fields for AMATEUR STATION, NAME, STREET ADDRESS, CITY, STATE, ZIP, and TELEPHONE NUMBER; a "FROM" section with fields for NAME, ADDRESS, CITY, STATE, ZIP, and TELEPHONE NUMBER; a "RECD" (Received) section with fields for DATE and TIME; and a "SENT" (Sent) section with fields for DATE and TIME. A red arrow points from the text "Use 'Received' (RECD) for origination on the standard form" to the "RECD" section. At the bottom, there is a disclaimer: "THIS MESSAGE WAS HANDLED FREE OF CHARGE BY A LICENSED AMATEUR RADIO OPERATOR. THE AMERICAN RADIO RELAY LEAGUE, INC. IS THE NATIONAL MEMBERSHIP SOCIETY OF..."

There's no radio stuff here, so you received it from a person, even if that person is a radio operator. You didn't get it from a station.

If you're a radio operator staffing W8SGT and originate a message that B. Jones verbally gave, you received the message from B. JONES/VERBAL, not from his callsign.




This isn't a tutorial on origination but her's one other thing to know so you have the concept.

The **STATION OF ORIGIN** is the station where the message was originated. In our example, it's W8SGT.

This radiogram in the station record at W8SGT clearly was originated for B. JONES, and came in verbally at 1405Z (10:05 A.M. EDT) on July 29.


“Tell them thanks for the coffee before mid-afternoon today!”



THE AMERICAN RADIO RELAY LEAGUE

RADIOGRAM

VIA AMATEUR RADIO



NUMBER	PRECEDENCE	HX	STATION OF ORIGIN W8SGT	CHECK	PLACE OF ORIGIN	TIME FILED	DATE
--------	------------	----	-----------------------------------	-------	-----------------	------------	------

TO _____

TELEPHONE NUMBER _____

THIS RADIO MESSAGE WAS RECEIVED AT

AMATEUR STATION _____ PHONE _____

NAME _____

STREET ADDRESS _____

CITY, STATE, ZIP _____

FROM _____

DATE _____

TIME _____

SENT _____

TO _____

DATE _____

TIME _____

THIS MESSAGE WAS HANDLED FREE OF CHARGE BY A LICENSED AMATEUR RADIO OPERATOR. THE AMERICAN RADIO RELAY LEAGUE, INC. IS THE NATIONAL MEMBERSHIP SOCIETY OF

Your callsign does not matter. This message was originated at W8SGT.

B. Jones might have a station callsign but it does not matter. This message was received from B. JONES, verbally, and has nothing to do with Jones' station.



This message needs action!

The parts of the radiogram format work together to provide not only accounting after the fact but to show the status of the message as it's being handled.

Relay

Move the message from one station to another station.

Relay moves the message from one station to another station.

The station that is holding the message must handle it.

The station holding the message will send it to another station.

The station receiving the message now holds it and must handle it.

Accounting happens at each step.



Relay: Send



Relay: Send to W8THV

W8SGT is on a net and lists to
W8OMR COLUMBUS.

W8OMR is not in the net.

Net control directs nearby
to take message for W8OMR.

W8THV calls W8SGT and
message.

W8SGT records station, date, and
saying ROGER (or sending "OK").

*This message at station W8SGT is not
handled.*

**Voice
Procedure for
Relay
Covered and
Practiced in
Next Session!**

THE AMERICAN RADIO RELAY LEAGUE
RADIOGRAM
VIA AMATEUR RADIO



STATION OF ORIGIN	CHECK	PLACE OF ORIGIN	TIME FILED	DATE
4 W8SGT	ARL 4	COLUMBUS OH	1423Z	JUL 29
C/O W8OMR		THIS RADIO MESSAGE WAS RECEIVED AT		
		AMATEUR STATION	PHONE	
		NAME		
		STREET ADDRESS		
		CITY, STATE, ZIP		
		THREE	COFFEE	
		C/O W8SGT COLUMBUS	43235	
SENT	TO	DATE	TIME	
1432Z	W8THV	JUL 29	1434Z	

THE AMERICAN RADIO RELAY LEAGUE, INC. IS THE NATIONAL MEMBERSHIP SOCIETY OF

at the time that it "leaves" the station.
W8THV operator said ROGER (or sent
"off" of W8SGT and "on" W8THV.

or should file the message where it stays
policy says. (Not 0 days, also probably not forever.)



Relay: Receive



This message now needs action at W8THV.

1. Relay to another station
2. Delivery to the addressee
3. Service (cancel this and originate new) message to STATION OF ORIGIN

Relay: Send



Relay: Send to W8OMR

W8THV is on a net and lists the traffic for W8OMR COLUMBUS.

W8OMR is in the net.

Net control directs W8OMR to take message from W8THV.

W8OMR calls W8THV and receives the message.

W8THV records station, date, and time saying ROGER (or sending "QSL").

This message at station W8THV is now handled.

THE AMERICAN RADIO RELAY LEAGUE RADIOGRAM VIA AMATEUR RADIO							
NUMBER	PRECEDENCE	HX	STATION OF ORIGIN	CHECK	PLACE OF ORIGIN	TIME FILED	DATE
42	P	B4	W8SGT	ARL 4	COLUMBUS OH	1423Z	JUL 29
TO				THIS RADIO MESSAGE WAS RECEIVED AT			
S4/HHC/4 C/O W8OMR				AMATEUR STATION			
COLUMBUS OH 43228				NAME			
TELEPHONE NUMBER				STREET ADDRESS			
				CITY, STATE, ZIP			
ARL				FIFTY			
THREE				COFFEE			
B JONES OHIO EMA C/O W8SGT COLUMBUS 43235							
REC'D W8SGT		JUL 29 1423Z		SENT TO W8OMR		JUL 29 1508Z	

THIS MESSAGE WAS HANDLED FREE OF CHARGE BY THE AMERICAN RADIO RELAY LEAGUE, INC. IS THE NATIONAL MEMBERSHIP SOCIETY OF

SENT is completed at the time that it "leaves" the station. This shows when W8THV operator said ROGER (or sent QSL). The message is "off" of W8THV and "on" W8OMR.

W8THV operator should file the message where it stays until policy says. (Not 0 days, also probably not forever.)



Relay: Receive





RADIOGRAM



Relay: Receive from W8THV

W8THV is on a net and lists the traffic for W8OMR COLUMBUS.

W8OMR is in the net.

Net control directs W8OMR to take message from W8THV.

W8OMR calls W8THV and receives the message.

W8OMR records station, date, and time operator said ROGER (or sending "QSL").

This message now needs action at W8OMR.

MSG. NO. 42	PRIORITY P	HX B4	STATION OF ORIGIN W8SGT ARL	CALL SIGN 4 COLUMBUS OH	PLACE OF ORIGIN OH	TIME (UTC) 1423Z	DATE JUL 29
TO: S4/HHC/4 C/O W8OMR							
COLUMBUS OH 43228							
MESSAGE: ARL FIFTY THREE COFFEE							
FROM (SIGNATURE): B JONES OHIO EMA C/O W8SGT							
COLUMBUS 43235							
RECEIVED FROM (CALL) W8THV	TIME JUL 29 1508Z	DATE	TRANSMITTED TO (CALL)	TIME	DATE	Form 1602	

This message at W8OMR clearly needs action:

1. RECD from W8THV (a station, i.e., radio)
2. TO is some other station
3. SENT is empty

Still must relay, deliver, or service.



Station W8OMR Take Action

W8OMR now has the message.

Station always decides which action to take:

1. Relay to another station
2. Deliver to the addressee, or
3. Service (cancel and notice).

Looking at “addressee” (TO),
we see it is directed to this station.

We do not use radio to relay this message
further.

We have all information needed here to
deliver.



RADIOGRAM



MSG. NO.	P	HX	B4	STATION OR ORIGIN	W8SGT ARL	4	PLACE OF ORIGIN	COLUMBUS OH	TIME (UTC)	1423Z	DATE	JUL 29
TO:		S4/HHC/4 C/O W8OMR								RECEIVED AT W8OMR		
		COLUMBUS OH 43228								S6/HHC/4CSSB OHMR		
										COLUMBUS OH 43228		
MESSAGE:		ARL FIFTY THREE COFFEE										
FROM (SIGNATURE):		B JONES OHIO EMA C/O W8SGT										
		COLUMBUS 43235										
RECEIVED FROM (CALL)		TIME		DATE		TRANSMITTED TO (CALL)		TIME		DATE		
W8THV				JUL 29 1508Z								

Since we are now delivering, we can now complete part 9 of the radiogram (“THIS MESSAGE WAS RECEIVED AT”), which is not preprinted on this form. Doesn’t matter. Goes in the same place.





RADIOGRAM



What's The Status?

W8OMR now has the message.

W8OMR can make delivery, no radio relay.

W8OMR has not yet made delivery.

SENT part is empty.

W8OMR needs to deliver this message!

Could be by phone if we know it,
Could be hand-delivery or courier,
Could be posted to site message board,
Could be intraoffice mail.

MSG. NO. 42	PRIORITY P	HX B4	STATION OR ORIGIN W8SGT ARL	CLASS 4	PLACE OF ORIGIN COLUMBUS OH	TIME (UTC) 1423Z	DATE JUL 29
TO:		S4/HHC/4 C/O W8OMR			RECEIVED AT W8OMR		
		COLUMBUS OH 43228			S6/HHC/4CSSB OHMR		
					COLUMBUS OH 43228		
MESSAGE:							
ARL		FIFTY		THREE		COFFEE	
FROM (SIGNATURE):		B JONES OHIO EMA C/O W8SGT					
		COLUMBUS 43235					
RECEIVED FROM (CALL)	TIME	DATE		TRANSMITTED TO (CALL)	TIME	DATE	
W8THV		JUL 29					

Form 1602

However it will get delivered, we know that delivery has not yet happened.



Delivery

Give the written message to the addressee (“To”), so it makes sense to them.

Delivery takes the relayed message and prepares it for the recipient.

The station that is holding the message must handle it.

No radio stuff!

Accounting continues.



Delivery: No More Radio

In this example, we deliver via internal email:

To: V.V. Resourceful
From: R.T. Operator
Date: Jul 29 11:17:31 EDT (-0400)
Subject: Radio Message from Ohio EMA

SGT:
Message for your shop follows. You
can send radio response through me.
V/R,
R.T. Operator PFC (OH), OHMR

291432Z JUL 20
TO S4/HHC/4
FR B JONES OHIO EMA
RECEIVED YOUR COFFEE. IT'S VERY MUCH
APPRECIATED; MANY THANKS.



RADIOGRAM



MSG. NO.	P	HX	B4 W8SGT ARL 4 COLUMBUS OH	1423Z JUL 29
----------	---	----	----------------------------	--------------

TO: S4/HHC/4 C/O W8OMR
COLUMBUS OH 43228

RECEIVED AT W8OMR
S6/HHC/4CSSB OHMR
COLUMBUS OH 43228

MESSAGE: ARL FIFTY THREE COFFEE

FROM (SIGNATURE): B JONES OHIO EMA C/O W8SGT
COLUMBUS 43235

Form 1602

RECEIVED FROM (CALL)	TIME	DATE	TRANSMITTED TO (CALL)	TIME	DATE
W8THV		JUL 29 1508Z	V.Resourceful/email		JUL 29 1517Z

Never just throw a message at the addressee. Calling someone up to say "ARL FIFTY I SPELL FOXTROT INDIA..." does no one any good.

You might attach a copy of the radiogram itself but in any case turn it back into something human readable.

When you make the delivery, it's SENT.

Delivery: No More Radio

In this example, we deliver via internal email:

To: V.V. Resourceful
From: R.T. Operator
Date: Jul 29 11:17:31 EDT (-0400)
Subject: Radio Message from Ohio EMA

SGT:
Message for your shop follows. You
can send radio response through me.
V/R,
R.T. Operator PFC (OH), OHMR

291432Z JUL 20
TO S4/HHC/4
FR B JONES OHIO EMA
RECEIVED YOUR COFFEE. IT'S VERY MUCH
APPRECIATED; MANY THANKS.



RADIOGRAM



MSG. NO.	P	HX	B4 W8SGT ARL 4 COLUMBUS OH	1423Z JUL 29
----------	---	----	----------------------------	--------------

TO: S4/HHC/4 C/O W8OMR
COLUMBUS OH 43228

RECEIVED AT W8OMR
S6/HHC/4CSSB OHMR
COLUMBUS OH 43228

MESSAGE: ARL FIFTY THREE COFFEE

FROM (SIGNATURE): B JONES OHIO EMA C/O W8SGT
COLUMBUS 43235

Form 1602

RECEIVED FROM (CALL)	TIME	DATE	TRANSMITTED TO (CALL)	TIME	DATE
W8THV		JUL 29 1508Z	V.Resourceful/email		JUL 29 1517Z



Delivery goes to a person, not a station;
this is the complement of origination.

Now the message is “off of” W8OMR, and it can be filed,
in accordance with the station policy. Probably not 0
days, but also not forever.

Recap

All of the parts together

RECD is when station receives the message:

- Origination if it's from a person
Often not by amateur radio
- Relay if it's from a station

SENT is when station sends the message:

- Relay if it's from a station
- Delivery if it's to a person
Often not by amateur radio



Question

What if the message came in over amateur radio but was informal?

Informal message (chatter) that results in the creation of a formal message (radiogram) is treated exactly as if a person spoke to a station operator.

Same as email to station operator.

Or phone call to station operator.

Origination is preparing for relay, making the formal message.



Proper Message Records Can Help Trace and Find Problems



THE AMERICAN RADIO RELAY LEAGUE
RADIOGRAM
VIA AMATEUR RADIO



NUMBER	PRECEDENCE	HX	STATION OF ORIGIN	CHECK	PLACE OF ORIGIN	TIME FILED	DATE
42	P	B4	W8SGT	ARL 4	COLUMBUS OH	1423Z	JUL 29

TO: S4/HHC/4 C/O W8OMR
COLUMBUS OH 43228

TELEPHONE NUMBER: _____

THIS RADIO MESSAGE WAS RECEIVED AT
AMATEUR STATION: _____ PHONE: _____
NAME: _____
STREET ADDRESS: _____
CITY, STATE, ZIP: _____

ARL FIFTY THREE COFFEE

B JONES OHIO EMA C/O W8SGT COLUMBUS 43235

FROM	DATE	TIME	TO	DATE	TIME
B. JONES/VERBAL	JUL 29	1405Z	SENT W8THV	JUL 29	1434Z

THIS MESSAGE WAS HANDLED FREE OF CHARGE BY A LICENSED AMATEUR RADIO OPERATOR. THE AMERICAN RADIO RELAY LEAGUE, INC. IS THE NATIONAL MEMBERSHIP SOCIETY OF

B JONES OHIO EMA C/O W8SGT COLUMBUS 43235

REC'D	DATE	TIME	SENT	DATE	TIME
W8SGT	JUL 29	1434Z	W8OMR	JUL 29	1508Z

THIS MESSAGE WAS HANDLED FREE OF CHARGE BY A LICENSED AMATEUR RADIO OPERATOR. THE AMERICAN RADIO RELAY LEAGUE, INC. IS THE NATIONAL MEMBERSHIP SOCIETY OF



LED: 13Z JUL 29

PHONE: _____

This is a key part of the job,
not a "nice to have."



RADIOGRAM

STATION OF ORIGIN	CHECK	PLACE OF ORIGIN	TIME FILED	DATE
W8SGT	ARL 4	COLUMBUS OH	1423Z	JUL 29

O W8OMR
TH 43228

RECEIVED AT W8OMR
S6/HHC/4CSSB OHMR
COLUMBUS OH 43228

TY THREE COFFEE

FROM (SIGNATURE):

B JONES OHIO EMA C/O W8SGT
COLUMBUS 43235

Form 1602

RECEIVED FROM (CALL)	TIME	DATE	TRANSMITTED TO (CALL)	TIME	DATE
W8THV		JUL 29 1508Z	V.Resourceful/email		JUL 29 1517Z



Thank You!

C. Matthew Curtin KD8TTE
youtube.com/KD8TTE

See Episode 008, *Radio
Message Accounting and Lifecycle
of a Radiogram*

